

# Yuasa Technical Data Sheet

Yuasa NP12-12 12V 12Ah - Yuasa NP series standby & cyclic AGM VRLA battery

## Specifications

Nominal Voltage (V)	12 V
10m rate Constant Power (Typ) to 9.6V at 20°C (/Block)	258.66
10m rate Constant Power (Typ) to 1.6V/cell at 20°C (/Cell)	43.11
20-hr rate Capacity to 1.75V /Cell at 20°C (Ah)	12
10-hr rate Capacity to 1.8V /Cell at 20°C (Ah)	11.1

## Dimensions

Length (mm)	151 (±1)
Width (mm)	98 (±1)
Height (mm)	97.5 (±1)
Weight (kg)	4.05

## Terminal Type

Terminal Type	Faston - 6.35mm
---------------	-----------------

## Operating Temperature Range

Storage (in fully charged condition)	-20°C to +60°C
Charge	-15°C to +50°C
Discharge	-20°C to +60°C

## Storage

Capacity loss per month at 20°C (% approx.)	3
---	---

## Case Material

Case Material	ABS (UL94:HB)
Standard or FR Case	Standard

## Charge Voltage

Float charge voltage at 20°C /Block (±1%)	13.65
Float charge voltage at 20°C /Cell (±1%)	2.275
Float Chg voltage tmp correction factor from std 20°C (mV)	-3
Cyclic (or Boost) charge Voltage at 20°C (V) /Block (±3%)	14.5
Cyclic (or Boost) charge Voltage at 20°C (V) /Cell (±3%)	2.42
Cyclic Chg voltage tmp correction factor from std 20°C (mV)	-4

## Charge Current

Float charge current limit (A)	3
Cyclic (or Boost) charge current limit (A)	3

## Maximum Discharge Current

Maximum discharge current 1s (A)	360
Maximum discharge current 1m (A)	75

## Short-Circuit Current & Internal Resistance


Short-Circuit current - according to EN IEC 60896-21 (A)	320
Internal resistance (mΩ) measured at 1 kHz	16

## Design Life & Approvals

EUROBAT Classification	Standard commercial: 3 to 5 years
Eurobat Life	3 to 5 years
Yuasa design life at 20°C (yrs)	Up to 5 years
VdS (Germany)	VdS_No: _G189170



## Layout



## Certifications

UNDERWRITERS LABORATORIES Inc.



## Safety

### Installation

Can be installed and operated in orientations up to 90° from the upright position.

### Handles

Batteries must not be suspended by their handles (where fitted).

### Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

### Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.



by GSYUASA

www.yuasa.com